

Product datasheet

Specifications



Easy UPS 1 Ph On-Line, 10kVA/ 10kW, Tower, 230V, 1x Hard wire 3- wire(1P+N+E) outlet, Intelligent Card Slot, LCD, Extended Runtime

SRVS10KIL

Overview

Presentation	For small to medium businesses, Easy UPS 1 Ph On-Line provides essential power protection for unstable power conditions, ensuring consistent and reliable connectivity at the most critical moments.
Lead time	Usually in Stock

Main

Main Input Voltage	230 V
Product or component type	Uninterruptible power supply (UPS)
Other Input Voltage	220 V 240 V
Main Output Voltage	230 V
Other Output Voltage	220 V 240 V
rated power in W	10000 W
rated power in VA	10000 VA
Output connector type	Hard wire 3-wire (1P + N + E) 1
Provided equipment	1 USB cable 1 RS-232 configuration cable 1 external battery pack 1 battery cable 1 user manual
Range of product	Easy UPS 1Ph On-Line

Batteries & Runtime

Run Time	View Runtime Graph
Efficiency	View Efficiency Graph
Battery type	Lead-acid battery
Battery voltage	240 V
Extended runtime	1
Number of battery filled slots	0
Number of battery free slots	0
Battery recharge time	5 h
Battery life	3...5 year(s)
Battery charger power	1170 W rated

General

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Number of power module filled slots	0
Number of power module free slots	0
Redundant	No

Physical

Colour	Black (RAL 7010)
Height	36.8 cm
Width	38 cm
Depth	48.5 cm
Net weight	76.5 kg
Mounting location	Front
Mounting preference	No preference
Mounting mode	Not rack-mountable
USB compatible	Yes
Mounting position	Vertical

Input

Input voltage limits	110...300 V half load 176...300 V full load
Number of input connectors	1 hard wire 3-wire (1P + N + E)
Network frequency	40...70 Hz auto sensing

Output

Maximum configurable power in VA	10000 VA
Maximum configurable power in W	10000 W
Output frequency	50/60 Hz +/- 3 Hz sync to mains
UPS type	Double conversion online
Wave type	Sine wave
Efficiency	94 % (full load)
Additional information	Configurable for 220 : 230 or 240 nominal output voltage
Bypass type	Internal bypass (automatic and manual)
Crest factor	3 : 1

Conformance

Product certifications	CE UKCA
Standards	EN/IEC 62040-1:2019/A11:2021 EN/IEC 62040-2:2006/AC:2006 EN/IEC 62040-2:2018

Environmental

Ambient air temperature for operation	0...40 °C
Relative humidity	0...95 % non-condensing

Operating altitude	0...3000 m
Ambient air temperature for storage	-15...60 °C
Storage Relative Humidity	0...95 % non-condensing
Storage altitude	0...15000 m
Acoustic level	58 dBA
Heat dissipation	2128 Btu/h
IP degree of protection	IP20

Communications & Management

Alarm	Alarm when on battery : distinctive low battery alarm : overload continuous tone alarm
Emergency power off	Yes
Free slots	1
control panel	Multifunction LCD status and control console

Surge Protection and Filtering

Surge energy rate	600 J
-------------------	-------

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	46.000 cm
Package 1 Width	58.000 cm
Package 1 Length	57.000 cm
Package 1 Weight	82.500 kg

Contractual warranty

Warranty	2 years repair or replace
----------	---------------------------



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

Use Better

Materials and Substances

[EU RoHS Directive](#)

Compliant with Exemptions

REACH Regulation

[REACH Declaration](#)

China RoHS Regulation

[China RoHS declaration](#)

Use Again

Repack and remanufacture

[Circularity Profile](#)

[End of Life Information](#)

Removable battery

User replaceable

WEEE

 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

Take-back

No